

903

MAST AMPLIFIERS

POWER SUPPLY 12 VDC 100 MA



Code : **9030087**

Model : **AL-105**

Description

Power supply units for mast amplifiers, 12 voltages. The power supply unit converts the mains supply into DC voltage and injects it into the coaxial cable to feed the amplifier. The signal coming from the antenna is distributed to its outputs. The power supply units are protected against overloads and short circuits. Available on request in 125 or 240 .

Applications

Individual digital and analogue terrestrial TV installations where mast amplifiers or antenna box preamplifiers are used. The feed voltage should be selected according to the amplifier installed.

Characteristics

Shielded zamak chassis, covered by an ABS plastic box for outdoor use. Power supply unit insulated from the high frequency circuit, complying with safety standards for both the installer and the user. Fixed to the wall by means of supplied wallplugs and screws. F type connectors. Supplied in individual or multiple packs.

Accessories

9120039 CM-004 Male F connector for Ø6.6 mm coaxial cable 9080023

MC-302 Male F connector for Ø7.0mm coaxial cable. 9120011 RS-275

Type F load of 75 Ω. 9040078 DI-007 DIN rail adaptor.

CODE		9030087		9030119		9030135	
MODEL			AL-105	AL-125		AL-205	
Connection			F female				
Inputs / outputs			1/2				
Frequency range	MHz		40-862				
Insertion loss	dB ±TOL	5/40-47 MHz	4.8±0.5				
		47-862 MHz	4.8±0.5				
		950-2150 MHz	-				
		2150-2400 MHz	-				
Output voltage	V $\overline{\sim}$		+12				
	mA		0-100			0-200	
Peak to peak ripple voltage	mV		-	<150			
Mains voltage	V \sim		230±10% 50/60 Hz				
	VA		7				
Operating temperature	°C		+5..+55				
Protection index			IP 30				
Units per packaging			24			24	
Packing weight	Kg		7.10			7.10	
Packing dimensions	mm		360 x 315 x 225			360 x 315 x 225	